




**CHARGE THE BATTERY BEFORE FIRST USE -**

(1) With Supplied cable, plug USB A connector to compliant powered port, (2) Swivel dust cover (on bottom) out of the way & lug the other end of the USB cable into the micro USB port. Allow 4 hours to charge.

## Bluetooth Keyboard (HID) Installation

### 1) Power On & Get to Know Your SP2100:

- Note SP2100's front Scan Button, & left side buttons. Press & hold the front Scan Button. SP2100 beeps & logo screen is replaced by the 3-line info screen.
- When the informational screen on the SP2100 disappears, it is important to note the Information Bar at the top of the screen.
- "MUX" Bluetooth Mode means the SP2100 is not connected and it is in "Discovery Mode".
- The SP2100 is ready to connect. **Select host OS below:**



#### **iPhone & iPad**

- Press "Settings", then "General" then "Bluetooth"
- Make sure the slider is "On"

#### **Android**

- Press "Settings", then "Wireless & Networks, check Bluetooth box.
- Select "Bluetooth Settings", then select "Scan for Devices"

#### **Windows**

- Press "Start", Devices & Printers
- Select "Add a Device"

Warranty on flyout of this card.

### 2) Select the SP2100 when it shows up on the host:




- In whatever host OS you're working, the scanner will show up as "SP2100-xxxxxxx". Either Highlight & press "next" in Windows or press in iOS or Android
- The SP-2100 will beep & the Information Bar on the scanner will change from "MUX" to "HID"

**YOUR SP2100 NOW WORKS AS A KEYBOARD WEDGE !**

OVER 

## Tips & Tricks....

- Press the bottom side button for 1 second on tablets / smart phones to make the keypad appear and disappear
- **By default, the SP2100 sends an <ENTER> key press at the end of the barcode.** See User's Guide to change this suffix.
- When the SP2100 is in sleep mode, press the scan button to wake it up, then again to activate the scanner / imager.
- Press the bottom side button for 3-5 seconds to disconnect / reconnect bluetooth to the host.
- Use the top side button to review the stored barcodes (see "SR" & "SN" Memory Data Mode below and in the User's Guide)
- **To access the SP2100 menu system, press and hold the upper side button.** Use the side buttons to highlight the option, then the Scan Button to enter the sub-menu. Here are some common options:
  - >>Settings>> lets you customize the Clock, Buzzer/Vibrator & display **your way!**
  - >>Memory>>Data Save>> "SR" = Send&Store, "SN" = StoreOnly, "PR" = "SendOnly"
  - >>Memory>>Data Save>>Memory>>Delete - Deletes all stored Scans
  - >>Bluetooth>>HID Batch - will stream all stored barcodes to host
- You can scan when away from your host. Press the bottom side button to connect Bluetooth, then select >>Bluetooth>>HID Batch from the Menu System.



The User's Guide has a complete list of instructions & explains each powerful option of your BarcodeGuy scanner. It can be found on our website. **HAVE FUN!! Email us and let us know how you're using & HOW YOU LIKE your new BarcodeGuy SP-2100 barcode scanner!!!**



Sales@BarcodeGuy.com

**Remember.... You can always get help - just call or email us.**

**WE LOVE PHONE CALLS!**

©Copyright 2012 - Carolina Barcode, Inc DBA BarcodeGuy.com

